



Read this document carefully before using this device. The guarantee will be expired by damaging of the device if you don't attend to the directions in the user manual. Also we don't accept any compensations for personal injury, material damage or capital disadvantages.

ENDA EUC742 PID UNIVERSAL CONTROLLER

Thank you for choosing ENDA EUC742 universal controller.

- * 72 x 72mm sized.
- * Selectable sensor type.
- * Selectable 0-20mA or 4-20mA input.
- * Automatic calculation of PID parameters (SELF TUNE).
- * Enter PID parameters of the system if they are known at the beginning. Otherwise, Self-Tune should be activated.
- * Soft-Start.
- * Communication via RS-485 ModBus protocol (Optional).
- * Selectable analog, SSR or relay control output.
- * Selectable 0-20mA or 4-20mA analog control output.
- * Relay output can be programmable as second alarm or control output.
- * AL1 relay output for first alarm out.
- * Selectable Heat/Cool control.
- * Input offset feature.
- * In the case of sensor failure periodical running or relay state can be selected.
- * Parameter or ModBus can be done through the control outputs.
- * Parameter access protection on 3 levels.
- * Programming by using keypad or Modbus.
- * CE marked according to European Norms.



RoHS
Compliant

TECHNICAL SPECIFICATIONS

Input type		Temperature range		Accuracy
		°C	°F	
PT100 Resistance Thermometer	EN 60751	-200...600 °C	-328... +1112 °F	± 0,2% (of full scale) ± 1 digit
PT100 Resistance Thermometer	EN 60751	-99.9...300.0 °C	-99.9...+543.0 °F	± 0,2% (of full scale) ± 1 digit
J (Fe-CuNi) Thermocouple	EN 60584	0... 600 °C	+32... +1112 °F	± 0,2% (of full scale) ± 1 digit
K (NiCr-Ni) Thermocouple	EN 60584	0...1200 °C	+32... +2192 °F	± 0,2% (of full scale) ± 1 digit
T (Cu-CuNi) Thermocouple	EN 60584	0... 400 °C	+32... +752 °F	± 0,2% (of full scale) ± 1 digit
S (Pt/Rh-Pt) Thermocouple	EN 60584	0...1600 °C	+32... +2912 °F	± 0,2% (of full scale) ± 1 digit
R (Pt13Rh-Pt) Thermocouple	EN 60584	0...1600 °C	+32... +2912 °F	± 0,2% (of full scale) ± 1 digit
0-20 mA	EN 60584	-999...4000		± 0,2% (of full scale) ± 1 digit
4-20 mA	EN 60584	-999...4000		± 0,2% (of full scale) ± 1 digit

ENVIRONMENTAL CONDITIONS

Ambient/storage temperature	0 ... +50 °C/-25... +70 °C (with no icing)		
Max. Relative humidity	80% up to 31 °C decreasing linearly 50% at 40 °C.		
Rated pollution degree	According to EN 60529	Front panel :	IP65
		Rear panel :	IP20
Height	Max. 2000m		



Do not use the device in locations subject to corrosive and flammable gases.

ELECTRICAL CHARACTERISTICS

Supply	90-250V AC, 50/60Hz or 9-30V DC/7-24V AC
Power consumption	Max. 7VA
Wiring	2.5mm ² screw-terminal connections
Line resistance	For thermocouple max.100ohm, for 3 wired PT100 max. 20ohm
Data retention	EEPROM (minimum 10 years)
EMC	EN 61326-1: 1997, A1: 1998, A2: 2001 (Performance criterion B for standard EN 61000-4-3)
Safety requirements	EN 61010-1: 2001 (Pollution degree 2, overvoltage category II)

OUTPUTS

CONT./AL2	Relay : 250V AC, 2A (for resistive load), NO/NC. Selectable as Control or Alarm2 output.
AL1	Relay : 250V AC, 2A (for resistive load), NO/NC selectable. (Alarm1 output).
ANL/SSR	Selectable as 0-20mA, 4-20mA analog output or logic control output.
Life expectancy for relay	Mechanical 30.000.000 operation; Electrical 300.000 operation

CONTROL



Control type	Single set-point and alarm control
Control algorithm	On-Off / P, PI, PD, PID (selectable)
A/D converter	15 bits
Sampling time	500ms
Proportional band	Adjustable between 0% and 100%. If Pb=0%, On-Off control is selected.
Integral time	Adjustable between 0.0 and 100.0 minutes
Derivative time	Adjustable between 0.00 and 25.00 minutes
Control period	Adjustable between 1 and 250 seconds
Hysteresis	Adjustable between 1 and 50 °C/F
Output power	The ratio of power at a set point can be adjusted between 0% and 100%

HOUSING

Housing type	Suitable for flush-panel mounting according to DIN 43 700.
Dimensions	W72xH72xD97mm
Weight	Approx. 395g (after packing)
Enclosure material	Self extinguishing plastics.





While cleaning the device, solvents (thinner, benzene, acid etc.) or corrosive materials must not be used.




Entering from the programming mode to the run mode:



If no key is pressed within 20 seconds during programming mode, the data is stored automatically and the run mode is entered.

Alternatively, the same function occurs first pressing  key and then pressing   keys together.

Page 2/5 →

ConF. Page 2/5



While holding  key, *run* message flashes. Then when  key is pressed, self tune mode is entered if there is no probe failure. If process value is appropriate to begin self tune, *rEdY* message flashes. Then press any key to see *P.idt.* message and self tune procedure begins.

Process value must be equal or lower than 60% of the setpoint to begin self tune procedure. If not, *t.EH* message flashes and device waits to decrease appropriate temperature to begin self tune. Then *rEdY* message flashes and press any key to begin self tune procedure.


Before self tune procedure, *R.tun* parameter must be selected *YES* from the *b.ECU* menu. If self tune is achieved *R.tun* parameter becomes *no* automatically and *b.tun* menu is canceled. Before self tune procedure, temperature setpoint value should be adjusted. When self tune procedure begins with no failure, *P.idt.* message flashes and remains during the calculation of PID parameters. When PID parameters are calculated, *P5Et.* message flashes. Then the device heats until setpoint value according to PID parameters and calculates the energy requirement for stable temperature and writes *P5Et.* parameter as % and run mode enters.

If any key is pressed while *P.idt.* message flashes, self tune procedure is deactivated before calculation of PID parameters. If any key is pressed while *P5Et.* message flashes, then self tune procedure is deactivated as PID parameters are calculated and *P5Et.* parameter is done.


TERMS

	<p>(1) Process value during normal operation Mnemonic parameter code during programming</p> <p>(2) Set point during normal operation. Data value during programming</p> <p>(3) Increment key during normal operation and programming Parameter selection key during programming</p> <p>(4) Decrement key during normal operation If only this key is pressed in normal operation, software version number is seen. Parameter selection key during programming</p> <p>(5) Alarm set key during normal operation Menu selection key during programming</p> <p>(6) Control set key during normal operation Parameter selection key during programming</p>
(1) PV display	4 digits 7 segment red LED
(2) SV display	4 digits 7 segment yellow LED
Character heights	PV display :14 mm SV display :10 mm
(3),(4),(5),(6) Keypad	Micro switch
(7) State indicator	3 red LEDs for Control, Alarm1 and SSR outputs

ALARM1 AND ALARM2 OUTPUT TYPES




MODIFICATION OF CONTROL AND ALARM SET POINTS



NOTE: The maximum of **C5Et** is the value of **CHIL** parameter and the minimum of it is the value of **CLoL** parameter.
 If independent alarm is selected, **R15E** and **R25E** values can be adjusted between the limits of the full scale.
 If deviation alarm is selected, **R15E** and **R25E** values can be adjusted between -300 and +300.
 If band alarm is selected, **R15E** and **R25E** values can be adjusted between 0 and +300.

Error Messages			
Temperature value is higher than the scale	Temperature value is lower than the scale	Temperature sensor is broken or over temperature	PT100 or a sensor line is short circuited

DIMENSIONS




- Note
- 1) While panel mounting, additional distance required for connection cables should be considered.
 - 2) Panel thickness should be maximum 10mm.
 - 3) If there is no 90mm free space at back side of the device, it would be difficult to remove it from the panel.

CONNECTION DIAGRAM



ENDA EUC742 is intended for installation in control panels. Make sure that the device is used only for intended purpose. The shielding must be grounded on the instrument side. During an installation, all of the cables that are connected to the device must be free of energy. The device must be protected against inadmissible humidity, vibrations, severe soiling and make sure that the operation temperature is not exceeded. All input and output lines that are not connected to the supply network must be laid out as shielded and twisted cables. These cables should not be close to the power cables or components. The installation and electrical connections must be carried on by a qualified staff and must be according to the relevant locally applicable regulations.




Logic output of the instrument is not electrically insulated from the internal circuits. Therefore, when using a grounding thermocouple, do not connect the logic output terminals to the ground.

- Note
- 1) Mains supply cords shall meet the requirements of IEC 60227 or IEC 60245.
 - 2) In accordance with the safety regulations, the power supply switch shall bring the identification of the relevant instrument and it should be easily accessible by the

NOTE :

SUPPLY :

90-250V ACV or
21.6-26.4V AC
50/60Hz 5VA




SENSOR INPUT :

For J-K-T-S-R type thermocouple :
Use suitable compensation cables. Don't use jointed cables. Pay attention to the polarities of the thermocouple cables as shown in the figure right are connected to the .

For resistance thermometer :
When 2 wired PT100 is used, terminals 7 and 8 must be short circuited.

Cable size: 1,5mm²



Holding screw
0.4-0.5Nm

Equipment is protected throughout
by DOUBLE INSULATION.

Order Code : EUC742--

1- Supply Voltage

230VAC...90-250V AC
SM.....9-30V DC / 7-24V AC

2- Modbus Option

RS.....RS-485 Modbus communication
None....No RS-485 Modbus communication